

## VOLTAGE DETECTOR EM18C



It is mainly used for detecting the presence of AC voltage in or around the object or surface and is very easy to operate.

AC voltage	About 12-100V (S button indicator is on) / About 48-100V (S button indicator is off)
Frequency	50Hz /60Hz
Alarm mode	Audiable alarm
Flashlight	White LED Lighting
Automatic shut down	√
Battery undervoltage indication	√
Zero line /fire line judgment	According to signal strength ,the strong signal is the fire line
NCV sensitivity	Automatically select 2 types of sensitivity (high,low)
NCV sensitivity indication method	The tester uses different alarm sounds of different frequencies and different color LED to indicate different sensitivity of high (red long),and low (green long)
Operating temperature	0-40 degrees
Storage temperature	10-50 degrees
Altitude	< 2000m
Security Level	CE CAT.III 1000V/CAT.IV 600V
Power supply	2x1.5V AAA Battery
Product size	160mmx23mmx26mm